

# Xerox® VersaLink® C400 Colour Printer



System Specification	VersaLink C400N	VersaLink C400DN
<b>One-Sided Speed</b> A4 / 210 x 297 mm	Up to 35 ppm colour and black-and-white	
<b>Two-Sided Speed</b> A4 / 210 x 297 mm	Up to 23 ppm colour and black-and-white	
<b>Monthly Duty Cycle</b> <sup>1</sup>	Up to 80,000 pages / month	
<b>Recommended Average Monthly Print Volume</b> <sup>2</sup>	Up to 5,000 pages	
<b>Processor</b>	1.05 GHz Dual-Core	
<b>Memory</b>	2 GB	
<b>Connectivity</b>	Ethernet 10/100/1000 Base-T High-speed USB 3.0 Wi-Fi 802.11n and Wi-Fi Direct with optional Wi-Fi Kit NFC Tap-to-Pair	
<b>Controller Features</b>	Unified Address Book, Configuration Cloning, Xerox Extensible Interface Platform®, Xerox® App Gallery, Xerox® Standard Accounting, Role Based Permissions, Convenience Authentication Enabled, Online Support (accessed from the user interface and print driver)	
Paper Handling	VersaLink C400N	VersaLink C400DN
<b>Bypass Tray</b>		
<b>Capacity</b> <sup>3</sup>	150 sheets	
<b>Sizes</b>	Custom Sizes: 76.2 x 127 mm to 216 x 356 mm	
<b>Weights</b>	60 – 220 gsm	
<b>Media Types</b>	Plain Lightweight Cardstock Cardstock Hole Punched Recycled Pre-Printed Letterhead Bond Lightweight Glossy Cardstock Glossy Cardstock Labels Envelopes Custom	
<b>Tray 1</b>		
<b>Capacity</b> <sup>3</sup>	550 sheets	
<b>Sizes</b>	Custom Sizes: 148 x 210 mm to 216 x 356 mm	
<b>Weights</b>	60 – 220 gsm	

# Xerox® VersaLink® C400 Colour Printer

Tray 1	
<b>Media Types</b>	Plain Lightweight Cardstock Cardstock Hole Punched Recycled Pre-Printed Letterhead Bond Lightweight Glossy Cardstock Glossy Cardstock Custom
Optional Tray 2	
<b>Capacity<sup>3</sup></b>	550 sheets
<b>Sizes</b>	Custom Sizes: 148 x 210 mm to 216 x 356 mm
<b>Weights</b>	60 – 220 gsm
<b>Media Types</b>	Plain Lightweight Cardstock Cardstock Hole Punched Recycled Pre-Printed Letterhead Bond Lightweight Glossy Cardstock Glossy Cardstock Custom
Total Capacity	
<b>Device Standard Capacity<sup>3</sup></b>	700 sheets
<b>Device Total Capacity<sup>3</sup></b>	1,250 sheets
Paper Output	
<b>Output Capacity<sup>3</sup></b>	250 sheets
<b>Automatic 2-Sided</b>	NA
	Standard
<b>Device Specification</b>	VersaLink C400N
	VersaLink C400DN
Electrical Requirements	
<b>Europe</b>	Voltage: 220-240 VAC+/- 10% Frequency: 50/60 Hz+/- 3Hz, 6 A
Power Consumption	
<b>Continuous Printing<sup>4</sup></b>	705 watts or less
<b>Ready (Standby) Mode<sup>4</sup></b>	76 watts or less
<b>Energy Saver (Sleep) Mode<sup>4</sup></b>	4 watts or less
Operating Environment	
<b>Required Temperature Range</b>	
Storage	0° C to 35° C
Operating	10° C to 32° C
<b>Required Relative Humidity</b>	10% to 85%
<b>Sound Power Levels</b>	Operating: 6.88 B(A) or less; Standby 5.0 B(A) or less
<b>Sound Pressure Levels</b>	Operating 53.1 dB(A) or less, Standby 29.2 dB(A) or less
<b>Boot Time (from Off to UI Ready)</b>	As fast as 60 seconds
<b>Warm-Up Time (from Power Save)</b>	As fast as 6 seconds

# Xerox® VersaLink® C400 Colour Printer

Dimensions and Weight (unpacked)	
<b>VersaLink C400N</b>	Width: 491 mm Depth: 488 mm Height: 399 mm Weight: 26 kg
<b>550-sheet Paper Tray</b>	Width: 427 mm Depth: 485 mm Height: 138 mm Weight: 3.9 kg
Dimensions and Weight (packaged)	
<b>VersaLink C400N</b>	Width: 627 mm Depth: 638 mm Height: 526 mm Weight: 30.45 kg
<b>550-sheet Paper Tray</b>	Width: 590 mm Depth: 544 mm Height: 241 mm Weight: 5.3 kg
System Certification/Regulatory Compliance	
<b>Certifications</b>	To view the latest list of certifications, go to <a href="http://www.xerox.com/OfficeCertifications">www.xerox.com/OfficeCertifications</a> .
<b>Print</b>	VersaLink C400N <span style="float: right;">VersaLink C400DN</span>
<b>First-Page-Out Time</b>	As fast as 13 seconds Colour / 12 seconds Black and White
<b>Resolution</b>	Up to 600 x 600 x 8 dpi (enhanced)
<b>Page Description Languages</b>	PCL® 5e, 6 PDF XPS TIFF JPEG HP-GL Adobe® PostScript® 3™
<b>Maximum Print Area</b>	4 mm from edge of paper
<b>Print Features</b>	Application Defaults Bi-directional Real-time Status Booklet Creation Draft Mode Job Identification Job Monitoring Personal Print Print from USB Sample Set Saved Job Scaling Secure Print Skip Blank Pages Store and Recall Driver Settings Two-sided Printing (as default - DN only) Xerox® Earth Smart Driver Settings
<b>Print from USB</b>	Allows walk-up printing from Type A USB port Supports direct printing from computer via Type B USB port Supported file formats: PDF, JPEG, TIFF, XPS, PDF/A
<b>Operating Systems</b>	Windows®, 7, 8, 10, Server 2000, Server 2003, Server 2008, Server 2008 R2 Server 2012 Mac OS® version 10.10, 10.11 & 10.12 Citrix Redhat® Enterprise Linux® IBM® AIX® 7.2 HP-UX® 11iv3 Oracle® Solaris 11.3 Fedora Core 24 SUSE® 13.2

# Xerox® VersaLink® C400 Colour Printer

Print	VersaLink C400N	VersaLink C400DN
<b>Network Protocols</b>	TCP/IP: HTTP/HTTPS, Internet Printing Protocol, LPR/LPD, Raw Socket Printing/Port 9100, IPv4/IPv6,WSD LDAP Bonjour® / AirPrint™ Secure FTP Most protocols not in use can be disabled	
<b>Administrative Protocols</b>	DHCP, SNMP, WINS, HTTP, HTTPS, TLS, SNTP, MDNS	
<b>Font Capability</b>	PostScript fonts: 144 PCL fonts: 82	
<b>Mobile Solutions and Mobile Device Apps</b>		
<b>Xerox® Mobile Express Driver®</b>	Makes it easy for mobile users to find, use and manage Xerox® and non-Xerox® devices in every new location. Plug into a new network, and Mobile Express Driver automatically discovers available printers and provides status and capability information. Save a list of “favorite” printers for each location, store application print settings for use on any printer in any network, and greatly reduce mobile support calls to IT.	
<b>Xerox® Global Print Driver®</b>	A truly universal print driver that lets IT administrators install, upgrade and manage Xerox® and non-Xerox® devices from a single driver. It provides a consistent, easy-to-use interface for end-users, reducing the number of support calls, and simplifying print services management.	
<b>Apple® AirPrint®</b>	Print email, photos and important office documents directly from an Apple iPhone® or iPad® with no drivers to install and no cables to connect. With AirPrint, an iPhone or iPad automatically locates and connects to the AirPrint-enabled device over the office Wi-Fi network.	
<b>Google Cloud Print™</b>	Google Cloud Print connects print devices to the web, enabling users to print the applications they use every day from smartphones, tablets, Chromebook™ notebook computers and any other web-connected device.	
<b>Xerox® Print Service Plug-in for Android™ (Free at Google Play™ Store)</b>	The Xerox® Print Service Plug-in for Android KitKat (4.4 or greater) devices streamlines mobile printing without third-party apps or additional print drivers. You can easily print photos, Web pages and documents when your mobile device is connected to multifunction printers using a wireless network. A robust print option set includes two-sided printing, stapling and secure code release. A free download is available from the Google Play™ store.	
<b>Software Solutions</b>		
<b>Xerox® ConnectKey® Apps (Found at the Xerox® App Gallery)</b>	Increase user productivity by simplifying and shortening everyday tasks. Unlike traditional software, ConnectKey Apps do not require a dedicated server, PC or IT resource. Instead, simply download these lightweight, serverless ConnectKey Apps to the device.	
<b>Security</b>	<b>VersaLink C400N</b>	<b>VersaLink C400DN</b>
<b>Security Features</b>	256-bit Encryption Access Controls Audit Log Automatic Self-Signed Certificate Creation Certificate Path Validation Certificate Revocation Settings Cisco® TrustSec Identity Services Engine (ISE) Integration Domain Filtering FIPS 140-2 Firmware Verification Immediate Disc Overwrite (with optional HDD) IP Address Filtering Network Authentication Port Filtering Role Based Permissions Secure Print Security Certificates Smart Card Enablement (CAC/PIV/.NET) SNMPv3 TLS	
<b>Xerox® PrintSafe Software (Optional)</b>	This authentication software integrates with trusted industry cards and readers and provides PIN access to nearly any printer in a customer’s secured print environment. It works with both Xerox® devices and devices from other vendors. This software is open to work with a variety of industry standard secure readers and cards.	
<b>Device Management</b>		
<b>Xerox® CentreWare® Web</b>		
	<ul style="list-style-type: none"> <li>• A Web-based server application for network administrators that permits web browser-based device management from any workstation, whether running Windows or UNIX or any other operating system</li> <li>• Works with any SNMP-managed printer from any manufacturer</li> <li>• Provides help with device discovery and installations, health checks and troubleshooting, and device upgrades, as well as basic accounting and asset management.</li> </ul>	
<b>Xerox® Embedded Web Server - Integrated Device Web Page</b>		
<b>Device Status</b>	Web server embedded <ul style="list-style-type: none"> <li>• Tray status/contents</li> <li>• Consumables status</li> </ul>	
<b>Print Queue Viewing</b>	Complete job print queue management—hold, release, promote and delete	

# Xerox® VersaLink® C400 Colour Printer

Xerox® Embedded Web Server - Integrated Device Web Page		
<b>Job Submission</b>	Print-ready files (PS, PCL, PDF, XPS, JPEG) Output feature selection	
<b>Device Administration</b>	Allows simple, remote installation setting of configuration options and management of the device	
<b>Browsers</b>	Microsoft® Internet Explorer® 11 Microsoft Edge™ 38 Mozilla™ Firefox® 48 Apple® Safari® 9.1 Google Chrome™ 52 Opera™ 39	
Remote Print Services		
<b>Automated Meter Reading (AMR)</b>	Automates the process of collecting and submitting meter reads for tracking and billing of Xerox® device usage. Eliminates the need for time-consuming end-user involvement and ensures that meter reads are submitted to Xerox on time.	
<b>Automated Supplies Replenishment (ASR)</b>	Automatically orders supplies for Xerox output devices based on actual usage, eliminating the need to manually manage supplies inventory.	
<b>Maintenance Assistant</b>	Offers a fast (and free) way to resolve potential issues and receive assistance and automate the troubleshooting/repair process. Diagnostic data is sent to Xerox®, allowing for problems to be solved faster with increased uptime.	
Accounting		
Xerox® Standard Accounting (Standard)		
<b>Tracking</b>	Print usage	
<b>Accounting</b>	Up to 9999 User Accounts with HHD installed Up to 1000 User Accounts without HHD installed (User ID) Up to 500 General accounts (Client)	
<b>Features</b>	<ul style="list-style-type: none"> <li>Administrator can manage the feature via the Web User Interface or device control panel in tools.</li> <li>Administrator has the ability to import or export user accounts, Group Accounts, General Accounts and User limits via an industry standard CSV file.</li> </ul>	
Accounting Options – Network Accounting (Allows central server to manage all accounting)		
	<ul style="list-style-type: none"> <li>Enhanced network accounting with up to the minute data on how the system is being used</li> <li>Comprehensive management and enterprise scale tracking and reporting of device usage of copy, print, scan and server fax</li> <li>Numerous solutions are available through Xerox Alliance Partners. For details visit <a href="http://www.xerox.com">www.xerox.com</a></li> <li>Security enhancements with the addition of HTTPS protocol support</li> <li>Device requests account authentication from third party server enabling larger databases of users and accounts</li> <li>Accept Authentication Login at control panel and pass to third party Networking Account</li> <li>Interface with third party accounting terminal for accounting user interface</li> </ul>	
What's In The Box		
	VersaLink C400 Color Printer Starter Capacity Print Cartridge: One of each (Cyan, Magenta, Yellow: 2,000 print capacity <sup>5</sup> , Black: 3,000 print capacity <sup>6</sup> ) Software and Documentation CD (Safety, Regulatory, Recycling and Disposal Guides, Print Drivers, and Warranty Statement) Installation Guide Quick Use Guides Power cord	
Supplies and Accessories	Quantity	Part Number
Supplies		
<b>Standard Capacity Toner Cartridges</b>	Cyan: 2,500 standard pages <sup>5</sup> Magenta: 2,500 standard pages <sup>5</sup> Yellow: 2,500 standard pages <sup>5</sup> Black: 2,500 standard pages <sup>5</sup>	106R03502 106R03503 106R03501 106R03500
<b>High Capacity Toner Cartridges</b>	Cyan: 4,800 standard pages <sup>5</sup> Magenta: 4,800 standard pages <sup>5</sup> Yellow: 4,800 standard pages <sup>5</sup> Black: 5,000 standard pages <sup>5</sup>	106R03518 106R03519 106R03517 106R03516
<b>Extra-High Capacity Toner Cartridges</b>	Cyan: 8,000 standard pages <sup>5</sup> Magenta: 8,000 standard pages <sup>5</sup> Yellow: 8,000 standard pages <sup>5</sup> Black: 10,500 standard pages <sup>5</sup>	106R03530 106R03531 106R03529 106R03528

# Xerox® VersaLink® C400 Colour Printer

Supplies and Accessories	Quantity	Part Number
<b>Supplies</b>		
<b>Drum Cartridge</b>	Cyan: 60,000 standard pages <sup>6</sup> Magenta: 60,000 standard pages <sup>6</sup> Yellow: 60,000 standard pages <sup>6</sup> Black: 60,000 standard pages <sup>6</sup>	108R01121
<b>Waste Cartridge</b>	30,000 standard pages <sup>6</sup>	108R01124
<b>Accessories</b>		
<b>550-sheet Paper Tray</b>		097S04400
<b>Productivity Kit with 320 GB HDD</b>		097S04914
<b>Stand</b>		497K13660
<b>Wireless Network Adapter</b>		497K16750

<sup>1</sup> Maximum volume capacity expected in any one month. Not expected to be sustained on a regular basis.

<sup>2</sup> Expected regular monthly throughput.

<sup>3</sup> Paper capacities are based on 20 lb. / 75 gsm stock; capacities will vary with different weight stocks.

<sup>4</sup> Power states defined per ENERGY STAR® Programme requirements for Imaging Equipment.

<sup>5</sup> Average standard pages. Declared Yield in accordance with ISO/IEC 19752. Yield will vary based on image, area coverage and print mode.

<sup>6</sup> Approximate pages. Declared Yield based on 3 A4-size 75 gsm pages. Yield will vary based on media type, size, weight, orientation, and usage patterns.

[www.xerox.com/office](http://www.xerox.com/office)

Configurations vary by geography.

©2017 Xerox Corporation. All rights reserved. Xerox®, Xerox and Design®, CentreWare®, ConnectKey® Global Print Driver®, MeterAssistant®, Mobile Express Driver®, SuppliesAssistant® and VersaLink® are trademarks of Xerox Corporation in the United States and/or other countries. As an ENERGY STAR® partner, Xerox Corporation has determined that this product meets the ENERGY STAR guidelines for energy efficiency (DN and DNI configurations). ENERGY STAR and the ENERGY STAR mark are registered U.S. marks. The information in this brochure is subject to change without notice.  
2/17 BR20954 - VC45S-01EA

